



ZLIS42

Integrated Step-Servo Motor Manual(PULSE CONTROL)

【 Please read the manual in detail before use, to avoid damage to the motor 】

Shenzhen ZhongLing Technology Co.,Ltd.

Add: 8th Floor, Building 3, Qiyu Industrial City, Gongle
Tiezai Rd., Xixiang St., Bao'an Dist, Shenzhen, China

Postcode: 518102

Tel: +86-0755-2979 9302

Fax: +86-0755-2912 4283

Email: sales@zlingkj.com

Web: www.zlingkj.com



CONTENTS

PREFACE	3
SAFETY PRECAUTIONS	3
1. PRODUCT INTRODUCTION	6
1.1 OUTLINE	6
1.2 FEATURES.....	6
1.3 APPLICATION	7
2. ELECTRICAL, ENVIRONMENTAL INDEX	7
2.1 ELECTRICAL INDEX	7
2.2 ENVIROMENTAL INDEX.....	7
2.3 INSTALLATION DIAGRAM.....	8
2.4 INSTALLATION	8
3. DRIVER INTERFACE AND WIRING	9
3.1 INTERFACE DEFINITION	9
3.2 CONTROL SIGNAL WIRING.....	10
3.3 OUTPUT SIGNAL WIRING.....	12
3.4 STATUS INDICATOR LED.....	12
4. DIP SWITCH SETTING	13
4.1 STEP RESOLUTION SETTING	13
4.2 MOTOR ROTATION DIRECTION SETTING.....	14

RELEASE NOTES:

Version	Update time	Update Content	Updater
V1.00	2018-10-12	First edition	LHY
V1.01	2019-9-28	1. Add wiring precaution in PREFACE; 2. Correct input voltage range in Chapter 1.2; 3. Add motor output holding torque in Chapter 2.1; 4. Add mechanical installation drawing in Chapter 2.3; 5. Modify step resolution in Chapter 3.1.2.	LHY
V1.02	2020-4-2	1. Update P/N from ZLIS42-P to ZLIS42	LHY
V1.03	2020-9-10	1. Update alarm indicator light in Chapter 3.4 STATUS INDICATOR LED	LHY
V1.04	2021-1-6	1. Update the power supply voltage range in Chapter 1.2 and Chapter 2.1; 2. Update power input port in Chapter 3.1.1; 3. Revise the subdivision description in Chapter 1.2 and Chapter 3.1.2; 4. Modify the interface content of in Chapter 1.2, Chapter 3.1.3 and Chapter 3.2 for hardware version is above V1.2.	LHY

PREFACE

Thank you for choosing ZLIS42 integrated step-servo motor.

This manual describes the installation, debugging, maintenance and operation of integrated step-servo motor ZLIS42. Please read this manual in detail before use, and be familiar with the safety precautions.

This manual may be revised timely when product is improved, specifications and version are changed or for some other reasons, which will not be notified particularly.

Any questions when using our products, please read the relevant manual or call our technical service department, we will meet your requirements in the shortest possible time.

Marks and warning signal:



Danger: Indicates that this operation error may endanger personal safety!



Attention: Indicates that this operation error may result in equipment damage!

SAFETY PRECAUTIONS

Open Box and Check



Do not install integrated step-servo motor which is damaged or with missing parts.

Installation



Installed on a non-flammable metal frame, prevent the intrusion of dust, corrosive gases, conductive objects, liquids and flammable materials, and

maintain good heat dissipation conditions.



During installation, be sure to tighten the mounting screws of the integrated step-servo motor. It should be protected from vibration and shock.

Wiring



Please perform the wiring work by professional electrical engineer;



Before wiring, please confirm that the input power is off. Wiring and inspection must be performed after the power is turned off and the integrated step-servo motor indicator is off to prevent electric shock;



When plugging and unplugging the integrated step-servo motor terminals, make sure that its indicator is off before proceeding;



Please set the emergent stop circuit outside the controller;



Please tighten the output terminal with a suitable torque.

Electrify



Please confirm whether the main circuit input power is consistent with the rated working voltage of the integrated step-servo motor;



Do not test the integrated step-servo motor for high voltage and insulation resistance at will;



Do not connect the electromagnetic contactor or electromagnetic switch to the output circuit.

Operation



Do not directly touch the output terminals after the integrated step-servo motor is powered on;



When the system is running, the integrated step-servo motor may have a high temperature rise, do not touch it;



Please confirm the input and output signals to ensure safe operation;




The alarm can be reset only after the operation signal is cut off. Alarm


resetting in the running signal state will cause the integrated step-servo motor to restart suddenly;


 *The alarm can be reset only after the operation signal is cut off. Alarm*


resetting in the running signal state will cause the integrated step-servo motor to restart suddenly;


Maintenance and Inspection


 *Do not touch the integrated step-servo motor terminals directly, and some have high voltage, very dangerous;*


 *Before powering up, be sure to install the cover; when removing the cover, be sure to cut off the power supply first;*


 *Before wiring, please confirm whether the input power is off;*


 *After cutting off the main circuit input power and confirming the integrated step-servo motor indicator light has completely extinguished, it can be inspected and maintained;*

 *Do the inspection and maintenance by professional electrical engineer;*

 *Do not do wiring, disassembling or other operation on the terminals during power on.*

 *Have a designated professional electrical engineer perform the inspection and maintenance work;*

 *During power-on, do not perform any work such as wiring or removing terminals.*

 *There is an integrated circuit on the main control board of the integrated step-servo motor. Please pay full attention when checking to avoid damage caused by static induction.*

1. PRODUCT INTRODUCTION

1.1. Outline

ZLIS42 is a 2 phase hybrid step-servo motor with high-performance digital integrated drive. The system has a simple structure and high integration. This series of integrated closed-loop stepper motors use the latest 32-bit dedicated DSP chip for motor control, and use advanced digital filter control technology, resonance vibration suppression technology and precise current control technology to enable the two-phase hybrid stepper motor to achieve precise and stable operation . This series of integrated closed-loop stepper motors have the characteristics of large torque output, low noise, low vibration, and low heat, which are especially suitable for electronic processing equipment, laser processing, medical and small numerical control equipment.

1.2. Features

- Full closed loop control, no step loss;
- Low vibration and noise;
- Maximum 512 microstep subdivision, minimum unit 2;
- Input voltage: 18V-36VDC;
- 3 isolated differential signal input ports: 3.3-24VDC;
- 1 isolated output port: alarm output, OC;
- The current control is smooth and accurate, and the motor has low heat generation;

- 4 DIP switch selection, 16-segment step resolution;
- With over-voltage, over-current, out of tolerance protect function etc;
- With built-in 1000-wire magnetic encoder, provides real-time feedback of motor running state.

1.3. Application

Suitable for all kinds of small automation equipment and instruments, such as: pneumatic marking machine, labeling machine, cutting machine, laser marking machine, plotter, small engraving machine, CNC machine tool, pick and place device. It is particularly effective in applications where users expect low noise, low vibration, high stationarity and high precision.

2. ELECTRICAL, ENVIRONMENTAL INDEX

2.1. Electrical Index

Driver Parameter	Min value	Typical value	Max value	Unit
Input voltage	18 VDC	24VDC	36VDC	V
Output current(peak)	0	1.2	2	A
Step signal frequency	0	-	200k	Hz
Control signal input current	7	10	16	mA
Over-voltage protection	-	50	-	VDC
Input signal voltage	-	5	-	VDC
Insulation resistance	100			MΩ
Encoder resolution		1000		Wires
Holding torque	L=70mm	0.48		N.m
	L=82mm	0.72		

2.2 Environmental Index

Cooling Type		Natural cooling or forced cooling
Working environment	Application occasion	Avoid dust, oil mist and corrosive gases
	Working temperature	0~50°C
	Max. ambient humidity	90% RH (no condensation)
	Storage temperature	-10~70°C
Vibration		10~55Hz/0.15mm

2.3 Installation Diagram





Fig.1 Installation dimension diagram (Unit: mm)

3. There are 2 options for L:70mm, 82mm. 2 options for $\varnothing D$: 5mm, 8mm.

2.4 Installation

User could mount with the mounting holes on the front of the integrated step-servo motor. Use M3 screw to install through the holes in the four corners. The integrated step-servo motor will generate heat. If continuous operation is under high input voltage and high power conditions, the effective heat dissipation area or forced cooling should be expanded. Do not use in places where air is not circulating or where the ambient temperature exceeds 60°C; do not install it in a place that is wet or has metal shavings.

3. DRIVER INTERFACE AND WIRING



3.1 Interface Definition

3.1.1 Power input port

Port	Pin	Mark	Name	Function
	6	DC	Power interface	Power supply 12-36V
	5	GND		
	4	NC	Floating interface	Normal: NC
	3	NC		
	2	NC		
	1	NC		

3.1.2 DIP switch

Port	Pin	Mark	Name	Function
	1	SW1	DIP switch	Motor direction selection
	2	SW2		Step resolution setting;
	3	SW3		Default value 2-512;
	4	SW4		Could be customized according to
	5	SW5		customer's demand.

3.1.3 Control signal port

Port	Pin	Mark	name	function
	1	PUL+	Pulse input	The default input voltage is 5V. For other voltages, current limiting resistors must be added, for example: 12V, external 1K 1 / 2W resistor, 24V, external 2K 1 / 2W resistor.
	2	PUL-		
	3	DIR+	Direction input	The default input voltage is 5V. For other voltages, current limiting resistors must be added, for example: 12V, external 1K 1 / 2W resistor, 24V, external 2K 1 / 2W resistor.
	4	DIR -		
	5	ENA+	Enable input	The default input voltage is 5V. For other voltages, current limiting resistors must be added, for example: 12V, external 1K 1 / 2W resistor, 24V, external 2K 1 / 2W resistor.
	6	ENA-		
	7	ALM+	Alarm input	Optically isolated OC output
	8	ALM-		

3.2 Control Signal Wiring

If input control signal is differential, its control signal interface wiring diagram is shown in Figure 2.




Fig.2 Control signal interface wiring diagram

If input control signal single-ended, its control signal interface wiring diagram is shown in Figure 3:




Fig.3 Input interface circuit

Note: The default input voltage of the control signal is 3.3-24V. For other voltages, current limiting resistors must be added. For example: 12V, external 1K 1 / 2W resistor; 24V, external 2K 1 / 2W resistor.

Control signal timing diagram

In order to avoid some malfunctions and deviations, PUL, DIR and ENA should meet certain requirements, as shown in the figure below:




Fig.4 Control signal timing diagram

Note:

1) t1: ENA (enable signal) should be confirmed to be high at least 100ms ahead of DIR, to ensure that the brake is open, and the motor enters running state, to avoid

abnormality.

- 2) t2: DIR is confirmed for its state to be high or low at least 5μs ahead of PUL falling edge.
- 3) t3: The pulse width is at least not less than 2.5μs.
- 4) t4: The low level width is not less than 2.5μs.

3.3. Output Signal Wiring

Signal output wiring, such as alarm signal output ALM, photoelectric isolation OC output, the highest withstand voltage 30VDC, the maximum saturation current 50mA.




Fig.5 Output Signal Wiring

3.4. Status Indicator LED

The green LED is the power indicator, which is always on when the driver is powered up; it is off when the driver is powered off. The red LED is the fault indicator. When the driver fails, it will stop and prompt the corresponding fault code. The fault can be cleared when the user needs to power off and restart the power. The status indicator LED represents different operation and fault information, as shown in the following table:


Status	Condition	Status indicator LED description	
over-current	The phase current through the motor exceeds the rated current or the phase-to-phase short circuit	1red	●
over-voltage	Power supply voltage exceeds maximum rated voltage	2red	●●

out-of-tolerance	Position out of tolerance	3red	
parameter read error	EEPROM read error	4red	
internal reference error	Driver internal fault	5red	

10000	OFF	ON	OFF	OFF
20000	ON	OFF	OFF	OFF
40000	OFF	OFF	OFF	OFF

4. DIP SWITCH SETTING

ZLIS42 uses a five-digit dial switch, set the step resolution accuracy and motor rotate direction. The detailed description is as follows:



4.1. Step resolution Setting

The step resolution parameters can be customized according to customer requirements, ranging from 400 to 51200 Step/Rev. For example, the default is the following table.

Step/Rev	SW2	SW3	SW4	SW5
400 (Default)	ON	ON	ON	ON
800	OFF	ON	ON	ON
1600	ON	OFF	ON	ON
3200	OFF	OFF	ON	ON
6400	ON	ON	OFF	ON
12800	OFF	ON	OFF	ON
25600	ON	OFF	OFF	ON
51200	OFF	OFF	OFF	ON
1000	ON	ON	ON	OFF
2000	OFF	ON	ON	OFF
4000	ON	OFF	ON	OFF
5000	OFF	OFF	ON	OFF
8000	ON	ON	OFF	OFF

4.2. Motor Rotation Direction Setting

SW1=off, the motor rotates counterclockwise (CCW);

SW1=on, clockwise rotation (CW).